

Web Advantage 3 Migration

This guide is designed to help with transferring your controller from previous webadv versions. If during the migration process you have trouble connecting to WebAdv3, please contact support at 918-686-6211.

There are (3) methods of transferring your MegaTron controller to Web Advantage 3:

- 1) Controller front panel
- 2) Classic WebAdv -or- 3) Enhanced WebAdv

Please Note: History does not transfer to WebAdv3 but will still be viewable on WebAdv2 with old login information.

Method 1: Controller Front Panel

Step 1:

Push the **SET UP RUN** button to get this screen. From here push **CONFIGURE** (Button 7) to go to the next screen.

```

>HOME SETUP<
SETPOINTS          DATE/TIME
CALIBRATION        CONFIGURE
TIMERS              HISTORY
CUSTOMIZE           WATER METER
ALARMS              RELAYS
  
```

Step 2:

This is the Configure Screen. From here push **NETWORK** (Button 8) to go to the next screen.

```

>CONFIGURE<
PASSWORD           CONTRAST
RELAYS              TEMP SCALE
                    NETWORK
HISTORY             SYS INFO
FLOW SW             FACTORY
  
```

Step 3:

This is the Network Summary Screen. Record the ACI SERVER value for troubleshooting. Press **SETTINGS** (Button 5) to continue.

```

>NETWORK<
IP ADDR: 192.168.1.76
SUBNET MASK: 255.255.255.0
GATEWAY: 192.168.1.240
DOMAIN: DynamicUniversal Rabbit BIO
ACI SERVER: web80.advantagecontrols.com
HOST: mycontroller
MAC: 00:90:c2:d9:ea:7c
DHCP: On
Local Mode: On
Remote Mode: On
SETTINGS          DHCP
                  RESET
  
```

Step 4:

This is the Configure Network Screen. From here push **SERVER** (Button 5) to go to the next screen.

```

>CONFIGURE NETWORK<
HTTP LOCAL
HTTP REMOTE
HOST
SERVER
  
```

Step 5:

Change the value ¹ to connect.webadvantage.online:80 If you are having trouble connecting use IP address 65.38.24.37:80 Press **ENTER** to confirm.

Note: Megatron / XS controller models containing the H card (i.e., XSCPF5-H), use :443 H1, H11, H21, H22, H31 models use :80

```

>CONFIGURE NETWORK<
WEB SERVER ADDRESS
[connect.webadvantage.online:80]
USE ARROW KEYS TO CHANGE, PRESS
ENTER TO ACCEPT OR BACK TO ERASE
SERVER
  
```

Step 6:

Press the **BACK** button. Press **RESET** (Button 0) and then press **ENTER**. A 60 second restart countdown will begin.

```

>NETWORK<
IP ADDR: 192.168.1.76
SUBNET MASK: 255.255.255.0
GATEWAY: 192.168.1.240
DOMAIN: DynamicUniversal Rabbit BIO
ACI SERVER: connect.webadvantage.online:80
HOST: mycontroller
MAC: 00:90:c2:d9:ea:7c
DHCP: On
Local Mode: On
Remote Mode: On
SETTINGS          DHCP
                  RESET
  
```

Step 7:

Login to http://webadvantage.online with your new, company administrator assigned, user id and password.

Step 8:

Find migrating controller in list of devices. If the controller is shown as **Online** (or in Alarm) you have successfully migrated to Web Advantage 3. If controller is not listed, check settings entered in Step 5 and proceed.

Web Advantage 3 Migration

Method 2: Web Advantage (Classic)

Step 1:

Login to Web Advantgatage - Classic:

<https://webadvantage.advantagecontrols.com/login.php>

Next, select controller and choose view.

Step 2:

Push the **SET UP RUN** button to get this screen. From here push **CONFIGURE** to go to the next screen.

```

>HOME SETUP<
SETPOINTS          DATE/TIME
CALIBRATION        CONFIGURE
TIMERS             HISTORY
CUSTOMIZE          WATER METER
ALARMS            RELAYS
  
```

Step 3:

This is the Configure Screen. From here push **NETWORK** to go to the next screen.

```

>CONFIGURE<
PASSWORD          CONTRAST
RELAYS            TEMP SCALE
HISTORY          NETWORK
FLOW SW          SYS INFO
FACTORY
  
```

Step 4:

This is the Interface Screen. From here push **INTERFACE 1** to go to the next screen.

```

>CONFIGURE NETWORK<
INTERFACE 1
  
```

Step 5:

This is the Network Summary Screen. Record the ACI SERVER value for troubleshooting. Press **SETTINGS** to continue.

```

>NETWORK<
IP ADDR: 192.168.1.76
SUBNET MASK: 255.255.255.0
GATEWAY: 192.168.1.240
DOMAIN: DynamiCUniversal Rabbit BIO
ACI SERVER: web80.advantagecontrols.com
HOST: mycontroller
MAC: 00:90:c2:d9:ea:7c
DHCP: On
SETTINGS          DHCP
RESET
  
```

Step 6:

This is the Configure Network Screen. From here push **SERVER** to go to the next screen.

```

>CONFIGURE NETWORK<
HTTP LOCAL
HTTP REMOTE
HOST
SERVER
  
```

Step 7:

Change the value ¹ to connect.webadvantage.online:80 If you are having trouble connecting use IP address 65.38.24.37:80 Press **ENTER** to confirm.

Note: Megatron / XS controller models containing the H card (i.e., XSCPF5-H), use :443 H1, H11, H21, H22, H31 models use :80

```

>CONFIGURE NETWORK<
WEB SERVER ADDRESS
[connect.webadvantage.online:80]
USE ARROW KEYS TO CHANGE, PRESS
ENTER TO ACCEPT OR BACK TO ERASE
SERVER
  
```

Step 8:

Press the **BACK** button. Press **RESET** (Button 0) and then press **ENTER**. A 60 second restart countdown will begin.

```

>NETWORK<
IP ADDR: 192.168.1.76
SUBNET MASK: 255.255.255.0
GATEWAY: 192.168.1.240
DOMAIN: DynamiCUniversal Rabbit BIO
ACI SERVER: connect.webadvantage.online:80
HOST: mycontroller
MAC: 00:90:c2:d9:ea:7c
DHCP: On
Local Mode: On
Remote Mode: On
SETTINGS          DHCP
RESET
  
```

Step 9:

Login to <http://webadvantage.online> with your new, company administrator assigned, user id and password.

Step 10:

Find migrating controller in list of devices. If the controller is shown as **Online** (or in Alarm) you have successfully migrated to Web Advantage 3. If controller is not listed, check settings entered in Step 7 and proceed.

Web Advantage 3 Migration

Method 3: Web Advantage (Enhanced)


Step 1:

Login to Web Advangtage - Enhanced:
<https://webadvantage.advantagecontrols.com/www/index.php>

Next, select controller and choose text view.


Step 2:

From the left menu, click on **CONFIGURE** to go to the next screen.




Step 3:

From here click on the **NETWORK** tab at the top of the page to go to the next screen.



Step 4:

This is the Network Summary Screen. Record the **SERVER** value for troubleshooting.



Step 5:

Change the value ¹ to connect.webadvantage.online:80
 If you are having trouble connecting use IP address
65.38.24.37:80

Note: Megatron / XS controller models containing the
H card (i.e., XSCPF5-H), use :443
H1, H11, H21, H22, H31 models use :80

Step 6:

Next, check the **RESET** box. Press **SUBMIT**. A 60 second restart countdown will begin. Browser will give a time-out error.

Step 7:

Login to <http://webadvantage.online> with your new, company administrator assigned, user id and password.

Step 8:

Find migrating controller in list of devices. If the controller is shown as **Online** (or in Alarm) you have successfully migrated to Web Advantage 3. If controller is not listed, check settings entered in Step 5 and proceed.

Notes:

¹ MegaTron XS controllers can use a connected USB keyboard to change values and navigate menus.